

## Multi-crystal oscillator

Written by Hans Summers

Monday, 03 April 2017 15:05 - Last Updated Monday, 03 April 2017 19:24

---

**Kostas SV3ORA** informed me of his oscillator circuit which has a single J108 Field Effect Transistor and three crystals, oscillating all at the same time on their three different frequencies. His article on this oscillator met with some scepticism. People thought that one crystal should dominate, ignoring the others. You can read the forum discussion that Kostas copy and pasted and has on his web page article.

**Kostas SV3ORA's triple crystal oscillator:** <http://grp.gr/multiosc/index.htm>

Personally I can't think of any practical uses for this right now in any of my current or future projects. But I was interested to try out the circuit and see for myself, what happens... and it shouldn't take too long, there aren't very many components to connect together, are there.

WRONG! Yes it's a simple circuit... but it is deceptive! It's a circuit that I feel I could spend days and days studying, or weeks, even. But I don't have days. So this is a simple write-up of what I did, with some points for further investigation another time (or by another person).

The first problem was that I didn't have a J108 FET. I do have some J310 FETs though. As Kostas pointed out, the J108 has a significant amount of gate-source capacitance. Therefore he didn't need to add any external capacitance, he could rely on the internal capacitance of the J108. He said a much lower capacitance device like the J310 should have maybe 150pF added across the gate to source leads. Actually in my case I found the J310 worked (2 crystals oscillating at the same time) even without the additional gate-source capacitance. My construction is rather messy. Nevertheless I don't think there would be a relatively significant amount of stray capacitance to make up the difference in gate-source capacitance.

Refer to the following circuit diagram:

# Multi-crystal oscillator

Written by Hans Summers

Monday, 03 April 2017 15:05 - Last Updated Monday, 03 April 2017 19:24



# Multi-crystal oscillator

Written by Hans Summers

Monday, 03 April 2017 15:05 - Last Updated Monday, 03 April 2017 19:24



Copyright © 2017 by Hans Summers. All rights reserved. This document is the property of Hans Summers. It is to be used only for personal use and not for distribution. It is to be kept confidential and not to be shared with others. It is to be kept secure and not to be lost. It is to be kept safe and not to be damaged. It is to be kept clean and not to be stained. It is to be kept neat and not to be messy. It is to be kept tidy and not to be cluttered. It is to be kept organized and not to be chaotic. It is to be kept professional and not to be unprofessional. It is to be kept accurate and not to be inaccurate. It is to be kept complete and not to be incomplete. It is to be kept correct and not to be incorrect. It is to be kept true and not to be false. It is to be kept honest and not to be dishonest. It is to be kept fair and not to be unfair. It is to be kept just and not to be unjust. It is to be kept kind and not to be unkind. It is to be kept gentle and not to be harsh. It is to be kept patient and not to be impatient. It is to be kept forgiving and not to be unforgiving. It is to be kept merciful and not to be merciless. It is to be kept gracious and not to be ungracious. It is to be kept generous and not to be ungenerous. It is to be kept helpful and not to be unhelpful. It is to be kept cooperative and not to be uncooperative. It is to be kept respectful and not to be disrespectful. It is to be kept courteous and not to be uncourteous. It is to be kept polite and not to be impolite. It is to be kept considerate and not to be inconsiderate. It is to be kept thoughtful and not to be unthoughtful. It is to be kept sensitive and not to be insensitive. It is to be kept empathetic and not to be unempathetic. It is to be kept understanding and not to be misunderstanding. It is to be kept tolerant and not to be intolerant. It is to be kept open-minded and not to be close-minded. It is to be kept flexible and not to be inflexible. It is to be kept adaptable and not to be unadaptable. It is to be kept resilient and not to be non-resilient. It is to be kept strong and not to be weak. It is to be kept confident and not to be unconfident. It is to be kept determined and not to be undetermined. It is to be kept motivated and not to be unmotivated. It is to be kept focused and not to be unfocused. It is to be kept disciplined and not to be undisciplined. It is to be kept organized and not to be disorganized. It is to be kept efficient and not to be inefficient. It is to be kept effective and not to be ineffective. It is to be kept successful and not to be unsuccessful. It is to be kept happy and not to be unhappy. It is to be kept healthy and not to be unhealthy. It is to be kept wealthy and not to be poor. It is to be kept powerful and not to be powerless. It is to be kept influential and not to be uninfluential. It is to be kept respected and not to be disrespected. It is to be kept loved and not to be unloved. It is to be kept admired and not to be unadmired. It is to be kept honored and not to be dishonored. It is to be kept revered and not to be unrevered. It is to be kept worshipped and not to be unworshipped. It is to be kept feared and not to be unfeared. It is to be kept respected and not to be disrespected. It is to be kept loved and not to be unloved. It is to be kept admired and not to be unadmired. It is to be kept honored and not to be dishonored. It is to be kept revered and not to be unrevered. It is to be kept worshipped and not to be unworshipped. It is to be kept feared and not to be unfeared. It is to be kept respected and not to be disrespected. It is to be kept loved and not to be unloved. It is to be kept admired and not to be unadmired. It is to be kept honored and not to be dishonored. It is to be kept revered and not to be unrevered. It is to be kept worshipped and not to be unworshipped. It is to be kept feared and not to be unfeared.

# Multi-crystal oscillator

Written by Hans Summers

Monday, 03 April 2017 15:05 - Last Updated Monday, 03 April 2017 19:24



Each crystal in the 0.004 MHz low gain oscillator is a 100 kHz oscillator. The first crystal is a 3.570 MHz

# Multi-crystal oscillator

Written by Hans Summers

Monday, 03 April 2017 15:05 - Last Updated Monday, 03 April 2017 19:24



## Multi-crystal oscillator

Written by Hans Summers

Monday, 03 April 2017 15:05 - Last Updated Monday, 03 April 2017 19:24

---

### Dual crystal oscillator output vs source resist



## Multi-crystal oscillator

Written by Hans Summers

Monday, 03 April 2017 15:05 - Last Updated Monday, 03 April 2017 19:24

---

### Dual crystal oscillator output vs source resi



### What didn't work...

I couldn't get three crystals to oscillate simultaneously the way Kostas did. I could observe at highest gain the highest frequency oscillating, then handing over to the next lower, then the lowest frequency crystal as I reduced the gain. But I could not find a point where all three oscillated at the same time.

Furthermore I could not succeed in getting EVERY pair of random crystals from my junkbox to oscillate simultaneously.

### Further investigation...

So clearly this oscillator really does operate on multiple crystal frequencies simultaneously. I feel that a lot more study could be done, to completely understand how it works and why; and what are the necessary conditions for it to work. As I said, I really don't have time now... but

## Multi-crystal oscillator

Written by Hans Summers

Monday, 03 April 2017 15:05 - Last Updated Monday, 03 April 2017 19:24

---

here is what I would like to investigate, if I did have time:

1. Effect of adding different amounts of gate-source capacitance to the J310
2. Effect of different amounts of capacitance to ground, or loading, at the other end of the crystal (where I put 10pF)
3. How to make three crystals oscillate together, as Kostas did?
4. Investigate a variable amount of series resistance (some 10's of ohms) in series with each crystal to try to equalise the activity of the crystals - which might make it easier to get them to oscillate together at the same time
5. What is the effect on the actual oscillation frequency of the crystal? Is it pulled some amount?
6. Use of a more linear buffer, to investigate the spectral purity of the oscillations